

HP 4193A			AIM 4170	
SRF .505			SRF .508	
KHZ	Z	PHASE	Z	PHASE
400	33000	66.0	34955	68.9
450	52000	46.0	57340	51.1
500	65000	4.0	68230	6.9
550	47000	-29.0	53360	-26.7
600	30000	-39.0	35240	-44.2
650	26000	-45.0	26060	-46.5
700	21000	-46.0	21490	-46.7
750	18000	-46.0	18820	-44.7
800	17110	-44.5	17480	-44.5
850	16200	-42.9	16290	-42.8
900	15770	-41.9	16140	-42.1
950	15700	-41.8	16110	-41.4
1000	15690	-42.6	15880	-43.5
1050	15740	-44.4	16208	-45.6
1100	15750	-46.6	16075	-47.7
1150	15670	-49.6	16090	-51.5
1200	15510	-52.9	15700	-56.4
1250	15170	-56.5	15575	-58.9
1300	14690	-59.9	14990	-62.6
1350	14050	-63.5	14135	-66.2
1400	13320	-66.6	13310	-66.9
1450	12560	-68.9	12460	-70.2
1500	11800	-70.8	11780	-71.9
1550	11080	-72.1	10950	-72.8
1600	10450	-72.8	10540	-74.2
1650	9860	-73.1	9800	-74.3
1700	9350	-73.3	9420	-74.0
1750	8950	-72.9	9070	-73.3
1800	8580	-72.2	8620	-73.2
1850	8320	-71.6	9435	-72.0
1900	8120	-70.9	8275	-71.8
1950	7980	-70.4	8030	-71.2
2000	7900	-70.0	7900	-71.3

